



ТЕХНИЧЕСКАЯ СПЕЦИФИКАЦИЯ

ITDAN-XR2

Dante - аналог (приемник)



Конвертер Dante - аналог (приемник)

Обзор

Конвертер из Dante в аналоговый сигнал, с разъёмами XLR. Не требует установки драйверов и программного обеспечения. Поддерживает 2 выходных канала аудио. Компактный дизайн и высокая производительность, питание от PoE.

Функции

- Компактный дизайн, простота в использовании, поддержка горячей замены
- Преобразование цифровых аудиосигналов Dante в аналоговые аудиосигналы
- 2 выходных аудиоканала
- Один кабель «витая пара» вместо нескольких аналоговых или многожильных кабелей, это экономично, эффективно и универсально
- Несжатые высококачественные аудиосигналы с почти нулевой задержкой
- Поддерживает программное обеспечение Dante, которое позволяет легко расширять и настраивать сеть и маршрутизацию звука
- Питание PoE.

| | |
|-----------------------|---|
| Max signal level | +18 dBu/+4 dBu/0 dBu 0 dBV/-10 dBV |
| Frequency Response | 20Hz to 20kHz(-/+0.5dB) |
| Impedance | 150 Ohm balanced 75 Ohm unbalanced |
| Dynamic Range | >100 dB |
| Signal-to-Noise Ratio | >100 dB |
| THD | <0.01% @+4 dBu |
| Dante | |
| Sample Rate | 44.1kHz, 48kHz, 96kHz |
| Bit Depth | 24 |
| Dante Device Latency | 1, 2 or 5ms (configurable using Dante Controller) |
| Model Name | Analog 0x2 |
| General | |
| Operation Temperature | -5 to +55°C (+23° to +131°F) |
| Storage Temperature | -25 to +70°C (-13° to +158°F) |
| Power | 802.3af PoE |
| Power Consumption | 2.6W(Max) |
| Dimension (W*H*D) | 30 x 28 x 114 mm |
| Cable length | 300mm |
| Net Weight | 145g |